

VOLTAGE CHART

VALVE	PIN 1	PIN 2	PIN 3	PIN 4	PIN 5	PIN 6	PIN 7	PIN 8
7B7	6V. D.C.	150V. D.C.	65 V. D.C.	2V. D.C.	0	- .7V. D.C.	2V. D.C.	0
7S7	0	2.5V D.C.	150V. D.C.	-13V. D.C.	65V. D.C.	- .7V. D.C.	2V. D.C.	6V. D.C.
7B7	6V. D.C.	215V. D.C.	65 V. D.C.	0	0	0	3.5V. D.C.	0
7C6	0	130V. D.C.	- .1V. D.C.	0	- .7V D.C.	- .7V. D.C.	0	6V. D.C.
6V6	0	6V. D.C.	185V. D.C.	215V. D.C.	0	215V. D.C.	0	11V D.C.
6X5	0	0	230V. AC.	0	230V. AC.	0	6V. D.C.	215V. D.C.

FOR 12V ALL VOLTAGES APPROX. THE SAME (.SEE NOTE)

BATT. DRAIN 6V 4.8 AMP.

BATT DRAIN 12 V. 3.6 AMP.

FOR 12V OPERATION A 12V VIB. REED IS USED AND THE FILAMENTS ARE WIRED IN SERIES PARALLEL , WITH THE NECESSARY SHUNTS ACROSS TUBES 7B7 R.F. AND 6V6 GT

ALIGNMENT INFORMATION

	DUMMY ANT.	FREQUENCY	TRIMMER	APPROX. SENSITIVITY
I.F.	.1MFD COND.	460 KC'S	T ₅ T ₆ T ₇ T ₈	200 μ V
R.F	STANDARD	1400 1000 600K	T ₁ T ₂ T ₃	2 μ V