


11/10/1944



VOLTAGE CHART

VALVE	PIN 1	PIN 2	PIN 3	PIN 4	PIN 5	PIN 6	PIN 7	PIN 8
6S7G	0	0	150 D.C.	55 D.C.	1.5 D.C.	0	6 A.C.	1.5 D.C.
7S7	6 A.C.	145 D.C.	55 D.C.	-6 D.C.	55 D.C.	0	1 D.C.	0
6S7G	0	0	150 D.C.	55 D.C.	1.5 D.C.	0	6 A.C.	1.5 D.C.
7C6	0	70 D.C.	-1 A.C.	0	-5 D.C.	0	0	6 A.C.
6G6G	0	0	150 D.C.	115 D.C.	0	0	6 A.C.	4 D.C.
6x5GT	0	0	150 A.C.	0	150 A.C.	0	6 A.C.	150 D.C.

RADIO (1936) L^{TD}

QUAY ST. AUCKLAND N.Z.

U. V. / A. C. / V. I. D.

R. A. J.

CIRCUIT	SUPERHETRODYNE
OPERATES FROM	220 - 230 VOLTS <u>A.C.</u> & <u>1/2</u> 6 VOLTS D.C.
POWER CONSUMED	20 WATTS
TUNING RANGE	1600 KC'S TO 550 KC'S
INTERMEDIATE FREQUENCY	460 KC'S
AUDIO POWER OUTPUT	.75 WATTS
SPEAKER	ROLA 6" 3.5 Ω IMPEDANCE