



STEWART "FIESTA"

TECHNICAL INFORMATION:

Frequency Range: 535 Kc/s - 1600 Kc/s

Intermediate Frequency: 455 Kc/s

Speakers: 2 Philips AD3800M

Valves: ECH81 Mixer

EF89 I.F. Amplifier

OA79 Audio Detector

2 x ECL82 Audio Amplifier and output
valve for each channel

EZ80 Rectifier

Supply Voltage: 270 V 50 C/S

Voltage Table:	V 1	Pin	1	75	Volts
			6	195	"
	V 2		8	75	"
			7	195	"
	V3	V 5	9	70	"
	V4	V 6	6	235	"
			7	200	"
			2	16	"
	V 7		3	300	"

Record Changer: B.S.R. U.A.14